

Factory Assembled Product Selection

NEMA Sizes 00 and 5⁽¹⁾

NEMA Size	Continuous Ampere Rating [A]	Maximum Horsepower Rating (Full Load Current Must Not Exceed Continuous Ampere Rating)						600V AC Maximum, 60 Hz		
		1-Phase Motor Voltage		3-Phase Motor Voltage				3 Power Poles Cat. No. ⁽²⁾	4 Power Poles Cat. No. ⁽²⁾	5 Power Poles Cat. No. ⁽²⁾
		115V	230V	200V	230V	380...415V	460...575V			
						50 Hz				
00	9	0.33	1	1.5	1.5	2	2	500-FO-930	—	—
0	18	1	2	3	3	5	5	(3)	(3)	(3)
1	27	2	3	7.5	7.5	10	10	(3)	(3)	(3)
2	45	3	7.5	10	15	25	25	(3)	(3)	(3)
3	90	7.5	15	25	30	50	50	(3)	(3)	(3)
4	135	—	—	40	50	75	100	500-FO-930	500-FO-940	—
5	270	—	—	75	100	150	200	—	—	—

(1) Includes a 120V AC coil and one N.O. auxiliary contact, as standard.

(2) The cat. nos. as listed are incomplete. Select a value from the Voltage Code table to complete each cat. no.
Example: To select a 120V AC coil voltage, Cat. No. 500-FO-930 becomes Cat. No. 500-FO930.

(3) See Base Contactor — NEMA Sizes 0...4 on page 6.

⊗ Voltage Code

Note: The base contactor includes a 120V AC coil as standard. For all other voltages, an alternate coil will be included in the modular kit for field installation.

[V]	24	110	120	125	208	220	240	250	277	380	415	440	480	550	600
AC, 50 Hz	J	D	—	—	—	—	—	—	—	—	—	—	B	—	C
AC, 60 Hz	J	—	D	—	H	—	A	—	F	—	—	—	—	—	—
DC ⁽¹⁾	VL	—	—	VG	—	—	—	VG	—	—	—	—	—	—	—

(1) DC coil voltages are only available for NEMA sizes 0...3. When ordering a DC coil voltage, add "DC" to the catalog number.
Example: 500DC-FOVL-930.