

Product Selection – Factory Assembled

NEMA Size 5⁽¹⁾

NEMA Size 5 ⁽¹⁾									
NEMA Size	Continuous Ampere Rating [A]	Maximum Horsepower Rating (Full Load Current Must Not Exceed Continuous Ampere Rating)							 600V AC Maximum, 60 Hz 3 Power Poles Cat. No. ⁽²⁾
		1-Phase Motor Voltage			3-Phase Motor Voltage				
		115V	230V	200V	230V	50 Hz	460...575V		
						380...415V			
0	18	1	2	3	3	5	5	(3)	
1	27	2	3	7.5	7.5	10	10	(3)	
2	45	3	7.5	10	15	25	25	(3)	
3	90	7.5	15	25	30	50	50	(3)	
4	135	—	—	40	50	75	100	(3)	
5	270	—	—	75	100	150	200	500F-F08930	

(1) Includes a 120V AC coil and one N.O. auxiliary contact, as standard.

(2) The cat. no. as listed is incomplete. Select a value from the Voltage Code table to complete the cat. no.
Example: To select a 120V AC coil voltage, Cat. No. 500F-F08930 becomes Cat. No. 500F-F0D930.

(3) See Base Contactor – NEMA Sizes 0...4 on page 10 for NEMA size 0...4 contactors.

⊗ Voltage Code

Note: The base contactor includes a 120V AC coil as standard. For all other voltages, an alternate coil will be included in the modular kit for field installation.

[V]	24	110	120	125	208	220	240	250	277	380	415	440	480	550	600
AC, 50 Hz	J	D	—	—	—	—	—	—	—	—	—	—	—	B	C
AC, 60 Hz	J	—	D	—	H	—	A	—	F	—	—	—	—	—	—